



FortiAnalyzer - Release Notes

Version 5.6.6

FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO GUIDE

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET COOKBOOK

<http://cookbook.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/support-and-training/training.html>

NSE INSTITUTE

<https://training.fortinet.com>

FORTIGUARD CENTER

<https://fortiguard.com/>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdocs@fortinet.com



October 04, 2018

FortiAnalyzer 5.6.6 Release Notes

05-566-514757-20181004

TABLE OF CONTENTS

Change Log	4
Introduction	5
Supported models	5
Minimum screen resolution	5
Special Notices	6
Mixed HA groups	6
Hyper-V FortiAnalyzer-VM running on an AMD CPU	7
IPsec connection to FortiOS for logging	7
Datasets Related to Browse Time	7
System Configuration or VM License is Lost after Upgrade	7
SSLv3 on FortiAnalyzer-VM64-AWS	8
Pre-processing logic of ebtime	8
Port 8443 reserved	8
Upgrade Information	9
Upgrading to FortiAnalyzer 5.6.6	9
ESX VM network mapping after upgrade	9
Downgrading to previous versions	9
Firmware image checksums	9
FortiAnalyzer VM firmware	10
SNMP MIB files	11
Product Integration and Support	12
FortiAnalyzer version 5.6.6 support	12
Feature support	14
FortiGate Management	15
Language support	15
Supported models	16
Resolved Issues	24
Event Management	24
FortiView	24
Log View	24
Reports	24
System Settings	25
Others	25
Common Vulnerabilities and Exposures	25
Known Issues	26
System settings	26

Change Log

Date	Change Description
2018-10-02	Initial release of 5.6.6.
2018-10-04	Added Mantis 473644 and 474994 to <i>Resolved Issues</i> .

Introduction

This document provides the following information for FortiAnalyzer version 5.6.6 build 1750:

- [Supported models](#)
- [Special Notices](#)
- [Upgrade Information](#)
- [Product Integration and Support](#)
- [Resolved Issues](#)
- [Known Issues](#)

For more information on upgrading your FortiAnalyzer device, see the *FortiAnalyzer Upgrade Guide*.

Supported models

FortiAnalyzer version 5.6.6 supports the following models:

FortiAnalyzer	FAZ-200D, FAZ-200F, FAZ-300D, FAZ-300F, FAZ-400E, FAZ-800F, FAZ-1000D, FAZ-1000E, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3700F and FAZ-3900E.
FortiAnalyzer VM	FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-AWS-OnDemand, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-OPC, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).

Minimum screen resolution

The recommended minimum screen resolution is 1280 x 800. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

Special Notices

This section highlights some of the operational changes that administrators should be aware of in FortiAnalyzer version 5.6.6.

Mixed HA groups

FortiAnalyzer uses the High Availability (HA) group name to create and register FortiGate devices in Device Manager. When multiple FortiGate clusters use the same group name, they appear as one, mixed cluster in the *Device Manager* pane in FortiAnalyzer GUI. The solution is to disable automatic grouping of HA members in FortiAnalyzer and clean up the mixed cluster.

Automatic grouping of HA members is enabled by default in FortiAnalyzer.

The following example describes how to clean up a mixed cluster in FortiAnalyzer that contains two FortiGate clusters.

To disable automatic grouping of HA members:

1. Log on to FortiAnalyzer and run the following command:

```
conf sys global
set ha-member-auto-grouping disable
end
```

To clean up the mixed cluster:

1. From FortiOS GUI, identify the High Availability (HA) primary and secondary members for the two clusters, according to the FortiGate HA infrastructure.
2. In FortiAnalyzer GUI, clean up the mixed HA cluster by deleting the HA members for the second HA cluster.
 - a. Go to *Device Manager*.
 - b. Right-click the HA cluster and select *Edit*.
 - c. Click the *Delete* icon to delete the members that do not belong to this cluster.

The result is one HA cluster with the required devices. The deleted devices for the second cluster are displayed in the *Unregistered device* list.

3. From FortiAnalyzer CLI, delete all the VDOM names from the mixed HA cluster by using the `exe log device vdom delete <Device Name> <VDOM>` command.
4. From FortiAnalyzer GUI, verify and promote unregistered devices to the second cluster.
 - a. Go to *Device Manager*, and verify that the deleted devices for the second HA cluster are displayed in the *Unregistered device* list as separate HA devices.
 - b. Promote the unregistered HA devices as HA devices.
5. In *Device Manager*, clean up the second cluster.
 - a. Right-click the secondary device in the second cluster, and select *Edit*.
 - b. Clear the *HA Cluster* check box to convert the secondary device to a standalone device.

- c. Right-click the primary device in the second cluster, and select *Edit*.
 - d. Add the secondary device back to the cluster.
6. In FortiAnalyzer, verify that there is a proper VDOM on the second cluster. If not, follow step 3 to delete the mixed VDOM by using the CLI.
7. From FortiAnalyzer GUI, go to *Device Manager*, and press F5 to load all the VDOMs into the GUI.

Hyper-V FortiAnalyzer-VM running on an AMD CPU

A Hyper-V FAZ-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

IPsec connection to FortiOS for logging

FortiAnalyzer 5.4.2 and later does not support an IPsec connection with FortiOS 5.0/5.2. However UDP or TCP + reliable are supported.

Instead of IPsec, you can use the FortiOS reliable logging feature to encrypt logs and send them to FortiAnalyzer. You can enable the reliable logging feature on FortiOS by using the `configure log fortianalyzer setting` command. You can also control the encryption method on FortiOS by using the `set enc-algorithm default/high/low/disable` command.

Datasets Related to Browse Time

If upgrading from an image prior to FAZ 5.4.2, cloned datasets that query for browse time may not be able to return any results after upgrade.

FortiAnalyzer 5.4.2 contains enhancements to calculating the estimated browse time. Due to the changes, cloned datasets that query for browse time may not be able to return any results after upgrade.

System Configuration or VM License is Lost after Upgrade

When upgrading FortiAnalyzer from 5.4.0 or 5.4.1 to 5.4.x or 5.6.0, it is imperative to reboot the unit before installing the 5.4.x or 5.6.0 firmware image. Please see the *FortiAnalyzer Upgrade Guide* for details about upgrading. Otherwise, FortiAnalyzer may lose system configuration or VM license after upgrade. There are two options to recover the FortiAnalyzer unit:

1. Reconfigure the system configuration or add VM license via CLI with `execute add-vm-license <vm license>`.
2. Restore the 5.4.0 backup and upgrade to 5.4.2.

SSLv3 on FortiAnalyzer-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiAnalyzer-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
    set ssl-protocol tlsv1
end
```

Pre-processing logic of ebtime

Logs with the following conditions met are considered usable for the calculation of estimated browsing time:

Traffic logs with `logid` of 13 or 2, when `logid == 13`, `hostname` must not be empty. The `service` field should be either HTTP, 80/TCP or 443/TCP.

If all above conditions are met, then `devid`, `vdom`, and `user` (`srcip` if `user` is empty) are combined as a key to identify a user. For time estimation, the current value of `duration` is calculated against history session start and end time, only un-overlapped part are used as the `ebtime` of the current log.

Port 8443 reserved

Port 8443 is reserved for `https-logging` from FortiClient EMS for Chromebooks.

Upgrade Information

Upgrading to FortiAnalyzer 5.6.6

You can upgrade FortiAnalyzer 5.4.0 or later directly to 5.6.6.

If you are upgrading from versions earlier than 5.4.0, you must upgrade to FortiAnalyzer 5.4 first. (We recommend that you upgrade to 5.4.5, the latest version of FortiAnalyzer 5.4.)



For details about upgrading your FortiAnalyzer, see *FortiAnalyzer Upgrade Guide*.

ESX VM network mapping after upgrade

Starting with FortiAnalyzer 5.6.0, Fortinet changed the network interface mapping as shown below. After upgrade to FortiAnalyzer 5.6.6, you must edit ESX VM network mapping in order to preserve network connectivity.

- port1 -> Network Adapter 1
- port2 -> Network Adapter 2
- port3 -> Network Adapter 3
- port4 -> Network Adapter 4

New FortiAnalyzer 5.6.0 and later VM installations use the correct mapping with ESX 5.5 and later.

Downgrading to previous versions

FortiAnalyzer does not provide a full downgrade path. You can downgrade to a previous firmware release via the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrading process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset all-settings
execute format {disk | disk-ext4}
```

Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. To verify the integrity of the download, select the *Checksum* link next to the *HTTPS* download link. A dialog box will be displayed with the image file name and checksum code. Compare this checksum with the checksum of the firmware image.

FortiAnalyzer VM firmware

Fortinet provides FortiAnalyzer VM firmware images for Amazon AWS, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

Citrix XenServer and Open Source XenServer

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.OpenXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- `.out.CitrixXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the Citrix XenServer Disk (VHD), and OVF files.

Linux KVM

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example `FAZ_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.hyperv.zip`: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Azure.

Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, `FAZ_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.hyperv.zip`: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.



Microsoft Hyper-V 2016 is supported.

VMware ESX/ESXi

- `.out`: Download either the 64-bit firmware image to upgrade your existing VM installation.
- `.ovf.zip`: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information see the FortiManager product data sheet available on the Fortinet web site, <http://www.fortinet.com/products/fortimanager/virtual-security-management.html>. VM installation guides are available in the [Fortinet Document Library](#).

SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiAnalyzer v5.00 file folder.

Product Integration and Support

FortiAnalyzer version 5.6.6 support

The following table lists FortiAnalyzer version 5.6.6 product integration and support information:

Web Browsers	<ul style="list-style-type: none">• Microsoft Internet Explorer version 11 or Edge 40 Due to limitation on Microsoft Internet Explorer or Edge, it may not completely render a page with a large set of policies or objects.• Mozilla Firefox version 62• Google Chrome version 69 <p>Other web browsers may function correctly, but are not supported by Fortinet.</p>
FortiOS/FortiOS Carrier	<ul style="list-style-type: none">• 5.6.0 to 5.6.6• 5.4.0 to 5.4.10• 5.2.0 to 5.2.13
FortiAnalyzer	<ul style="list-style-type: none">• 5.6.0 and later• 5.4.0 and later• 5.2.0 and later• 5.0.0 and later
FortiCache	<ul style="list-style-type: none">• 4.2.8• 4.1.6• 4.0.4
FortiClient	<ul style="list-style-type: none">• 5.6.0 and later• 5.4.0 and later• 5.2.0 and later• 5.0.4 and later
FortiMail	<ul style="list-style-type: none">• 5.4.7• 5.3.12• 5.2.10• 5.1.7• 5.0.10
FortiManager	<ul style="list-style-type: none">• 5.6.0 and later• 5.4.0 and later• 5.2.0 and later• 5.0.0 and later

- | | |
|---------------------|---|
| FortiSandbox | <ul style="list-style-type: none">• 2.5.2• 2.5.0• 2.4.1• 2.4.0• 2.3.3• 2.3.2• 2.2.2• 2.1.3• 2.0.3• 1.4.0 and later• 1.3.0• 1.2.0 and 1.2.3 |
|---------------------|---|

- | | |
|--------------------|---|
| FortiSwitch | <ul style="list-style-type: none">• 5.2.5 |
|--------------------|---|

- | | |
|-----------------|---|
| FortiWeb | <ul style="list-style-type: none">• 5.9.1• 5.8.6• 5.8.3• 5.8.1• 5.8.0• 5.7.2• 5.6.1• 5.5.6• 5.4.1• 5.3.9• 5.2.4• 5.1.4• 5.0.6 |
|-----------------|---|

- | | |
|------------------|--|
| FortiDDoS | <ul style="list-style-type: none">• 4.6.0• 4.5.0• 4.4.2• 4.3.2• 4.2.3• 4.1.12 |
|------------------|--|

- | | |
|---------------------------|---|
| FortiAuthenticator | <ul style="list-style-type: none">• 5.2.2• 5.1.2• 5.0.0• 4.3.4• 4.2.1• 4.1.2• 4.0.1 |
|---------------------------|---|

Virtualization

- Amazon Web Service AMI, Amazon EC2, Amazon EBS
- Citrix XenServer 7.2
- Linux KVM Redhat 7.1
- Microsoft Azure
- Microsoft Hyper-V Server 2002 and 2016
- OpenSource XenServer 4.2.5
- VMware ESXi versions 5.0, 5.5, 6.0, 6.5 and 6.7



Always review the Release Notes of the supported platform firmware version before upgrading your device.

Feature support

The following table lists FortiAnalyzer feature support for log devices.

Platform	Log View	FortiView	Event Management	Reports
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓
FortiAnalyzer	✓		✓	
FortiAuthenticator	✓			
FortiCache	✓		✓	✓
FortiClient registered to FortiGate	✓	✓		✓
FortiClient registered to FortiClient EMS	✓	✓		✓
FortiDDoS	✓	✓	✓	✓
FortiMail	✓		✓	✓
FortiManager	✓		✓	
FortiSandbox	✓		✓	✓
FortiWeb	✓		✓	✓
Syslog	✓		✓	

FortiGate Management

You can enable FortiManager features on some FortiAnalyzer models. FortiAnalyzer models with FortiManager features enabled can manage a small number of FortiGate devices, and all but a few FortiManager features are enabled on FortiAnalyzer. The following table lists the supported modules for FortiAnalyzer with FortiManager Features enabled:

FortiManager Management Modules	FortiAnalyzer with FortiManager Features Enabled
Device Manager, except firmware and license management	✓
Policy & Objects	✓
AP Manager	✓
FortiClient Manager	✓
VPN Manager	✓
FortiGuard	
FortiMeter	
FGT-VM License Activation	
Chassis Management	✓
High Availability	✓

Language support

The following table lists FortiAnalyzer language support information.

Language	GUI	Reports
English	✓	✓
Chinese (Simplified)	✓	✓
Chinese (Traditional)	✓	✓
French		✓
Hebrew		✓
Hungarian		✓
Japanese	✓	✓
Korean	✓	✓
Portuguese		✓

Language	GUI	Reports
Russian		✓
Spanish		✓

To change the FortiAnalyzer language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language from the drop-down list. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages and import the language translation files into FortiAnalyzer by using one of the following commands:

```
execute sql-report import-lang <language name> <ftp> <server IP address> <user name>
    <password> <file name>
execute sql-report import-lang <language name> <sftp> <server IP address> <user name>
    <password> <file name>
execute sql-report import-lang <language name> <scp> <server IP address> <user name>
    <password> <file name>
execute sql-report import-lang <language name> <tftp> <server IP address> <file name>
```

For more information about commands, see the *FortiAnalyzer CLI Reference*.

Supported models

The following tables list which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiManager, FortiWeb, FortiCache, and FortiSandbox models and firmware versions can log to a FortiAnalyzer appliance running version 5.6.6. Please ensure that the log devices are supported before completing the upgrade.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

FortiGate models

Model	Firmware Version
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG-200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG-300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E, FortiGate 5000 Series: FG-5001C, FG-5001D FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-XEN, FG-VMX-Service-Manager, FOSVM64, FOSVM64-KVM FortiGate Rugged: FGR-30D, FGR-35D, FGR-60D, FGR-90D FortiManager: FMG-200D, FMG-200F, FMG-300D, FMG-300E, FMG-400E, FMG-1000D, FMG-2000E, FMG-3000F, FMG-3900E, FMG-4000D, and FMG-4000E FMG-VM64, FMG-VM64-AWS, FMG-VM64-Azure, FMG-VM64-HV (including Hyper-V 2016), FMG-VM64-KVM, and FMG-VM64-XEN (for both Citrix and Open Source Xen).	5.6

Model	Firmware Version
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-DSL, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-200E, FG-201E, FGT-300D, FGT-300E, FGT-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG 3800D, FG-3810D, FG-3815D, FG-3960E, FG3980E, FG-2000E, FG-2500E FortiGate 5000 Series: FG-5001C, FG-5001D, FG-5001E, FG-5001E1 FortiGate 6000 Series: FG-6000F, FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiGate 7000 Series: FG-7030E-Q, FG-7030E-S, FG-7040E-1, FG-7040E-2, FG-7040E-3, FG-7040E-4, FG-7040E-5, FG-7040E-6, FG-7040E-8, FG-7040E-8-DC, FG-7060E-1, FG-7060E-2, FG-7060E-3, FG-7060E-4, FG-7060E-5, FG-7060E-6, FG-7060E-8 FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E-DSL, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM FortiGate Rugged: FGR-30D, FGR-30D-ADSL-A, FGR-35D, FGR-60D, FGR-90D	5.4

Model	Firmware Version
FortiGate: FG-20C, FG-20C-ADSL-A, FG-30D, FG-30D-POE, FG-40C, FG-60C, FG-60C-POE, FG-60C-SFP, FG-60D, FG-60D-3G4G-VZW, FG-60D-POE, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-90D, FG-90D-POE, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-110C, FG-111C, FG-140D, FG-140D-POE, FG-140D-POE-T1, FG-200B, FG-200B-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-300C, FG-300D, FG-310B, FG-311B, FG-400D, FG-500D, FG-600C, FG-600D, FG-620B, FG-621B, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1240B, FG-1500D, FG-1500DT, FG-3000D, FG-3016B, FG-3040B, FG-3100D, FG-3140B, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3810A, FG-3810D, FG-3815D, FG-3950B, FG-3951B FortiGate 5000 Series: FG-5001A, FG-5001A-SW, FG-5001A-LENC, FG-5001A-DW-LENC, FG-5001A-SW-LENC, FG-5001B, FG-5001C, FG-5001D, FG-5101C FortiGate DC: FG-80C-DC, FG-300C-DC, FG-310B-DC, FG-600C-DC, FG-620B-DC, FG-621B-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1240B-DC, FG-1500D-DC, FG-3000D-DC, FG-3040B-DC, FG-3100D-DC, FG-3140B-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3810A-DC, FG-3810D-DC, FG-3815D-DC, FG-3950B-DC, FG-3951B-DC FortiGate Low Encryption: FG-20C-LENC, FG-40C-LENC, FG-60C-LENC, FG-80C-LENC, FG-100D-LENC, FG-200B-LENC, FG-300C-LENC, FG-310B-LENC, FG-600C-LENC, FG-620B-LENC, FG-1000C-LENC, FG-1240B-LENC, FG-3040B-LENC, FG-3140B-LENC, FG-3810A-LENC, FG-3950B-LENC FortiWiFi: FWF-20C, FWF-20C-ADSL-A, FWF-30D, FWF-30D-POE, FWF-40C, FWF-60C, FWF-60CM, FWF-60CX-ADSL-A, FWF-60D, FWF-60D-3G4G-VZW, FWF-60D-POE, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate Rugged: FGR-60D, FGR-100C FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWSONDEMAND, FG-VM-Azure, FG-VM64-HV, FG-VM64-KVM, FG-VM64-XEN FortiSwitch: FS-5203B, FCT-5902D	5.2

FortiCarrier Models

Model	Firmware Version
FortiCarrier: FCR-3000D, FCR-3100D, FCR-3200D, FCR-3700D, FCR-3700DX, FCR-3800D, FCR-3810D, FCR-3815D, FCR-5001C, FCR-5001D, FCR-3000D-DC, FCR-3100D-DC, FCR-3200D-DC, FCR-3240C, FCR-3600C, FCR-3700D-DC, FCR-3810D-DC, FCR-5001C FortiCarrier DC: FCR-3000D-DC, FCR-3100D-DC, FCR-3200D-DC, FCR-3240C-DC, FCR-3600C-DC, FCR-3700D-DC, FCR-3810D-DC, FCR-3815D-DC FortiCarrier VM: FCR-VM, FCR-VM64, FCR-VM64-AWS, FCR-VM64-AWSONDEMAND, FCR-VM64-HV, FCR-VM64-KVM	5.4

Model	Firmware Version
FortiCarrier: FCR-3000D, FCR-3100D, FCR-3200D, FCR-3240C, FCR-3600C, FCR-3700D, FCR-3700DX, FCR-3810A, FCR-3810D, FCR-3815D, FCR-3950B, FCR-3951B, FCR-5001A, FCR-5001B, FCR-5001C, FCR-5001D, FCR-5101C, FCR5203B, FCR-5902D FortiCarrier DC: FCR-3000D-DC, FCR-3100D-DC, FCR-3200D-DC, FCR-3700D-DC, FCR-3810D-DC FortiCarrier Low Encryption: FCR-5001A-DW-LENC FortiCarrier VM: FCR-VM, FCR-VM64, FCR-VM64-HV, FCR-VM64-KVM, FCR-Vm64-XEN, FCR-VM64-AWSONDEMAND	5.2

FortiDDoS models

Model	Firmware Version
FortiDDoS: FI-200B, FI-400B, FI-600B, FI-800B, FI-900B, FI-1000B, FI-1200B, FI-2000B	4.2, 4.1, 4.0

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, and FAZ-3900E. FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	5.6
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, and FAZ-4000B. FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-XEN (Citrix XenServer and Open Source Xen), FAZ-VM64-KVM, and FAZ-VM64-AWS.	5.4
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-200E, FAZ-300D, FAZ-400C, FAZ-400E, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, FAZ-4000B FortiAnalyzer VM: FAZ-VM, FAZ-VM-AWS, FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-XEN	5.2
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-200E, FAZ-300D, FAZ-400B, FAZ-400C, FAZ-400E, FAZ-1000B, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000A, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-4000A, FAZ-4000B FortiAnalyzer VM: FAZ-VM, FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM-KVM, FAZ-VM-XEN	5.0

FortiMail models

Model	Firmware Version
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000E, FE-3200E FortiMail Low Encryption: FE-3000C-LENC	5.4.5
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000D, FE-3000E, FE-3200E, FE-5002B FortiMail Low Encryption: FE-3000C-LENC FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.3.12
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5002B FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.2.10
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.1.7
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-1000D, FE-2000A, FE-2000B, FE-3000C, FE-3000D, FE-4000A, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.0.10

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox VM: FSA-KVM, FSA-VM	2.5.2
FortiSandbox: FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox VM: FSA-VM	2.4.1 2.3.3
FortiSandbox: FSA-1000D, FSA-3000D, FSA-3500D FortiSandbox VM: FSA-VM	2.2.2 2.1.3
FortiSandbox: FSA-1000D, FSA-3000D FortiSandbox VM: FSA-VM	2.0.3 1.4.2
FortiSandbox: FSA-1000D, FSA-3000D	1.4.0 and 1.4.1 1.3.0 1.2.0 and later

FortiSwitch ACTA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5902D, FTCL-5903C, FTCL-59	5.2.0

Model	Firmware Version
FortiSwitch-ATCA: FS-5003A, FS-5003B FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	5.0.0
FortiSwitch-ATCA: FS-5003A, FS-5003B	4.3.0 4.2.0

FortiWeb models

Model	Firmware Version
FortiWeb: FWB-1000D, FWB-1000E, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-CMINTF, FWB-HYPERV, FWB-KVM, FWB-KVM-PAYG, FWB-VM, FWB-VM-PAYG, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.9.1
FortiWeb: FWB-1000C, FWB-1000D, FWB-1000E, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-Azure-Ondemand, FWB-CMINTF, FWB-HYPERV, FWB-KVM, FWB-KVM-PAYG, FWB-VM, FWB-VM-PAYG, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.8.6
FortiWeb: FWB-1000C, FWB-1000D, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-HYPERV, FWB-KVM, FWB-OS1, FWB-VM, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.7.2
FortiWeb: FWB-1000C, FWB-1000D, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D FortiWeb VM: FWB-Azure, FWB-HYPERV, FWB-KVM, FWB-VM, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.6.1
FortiWeb: FWB-100D, FWB-400C, FWB-400D, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM-64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVER, FWB-HYPERV, FWB-KVM, FWB-AZURE	5.5.6
FortiWeb: FWB-100D, FWB-400C, FWB-1000C, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVER, FWB-HYPERV	5.4.1

Model	Firmware Version
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, and FWB-HYPERV	5.3.9
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E FortiWeb VM: FWB-VM64, FWB-HYPERV, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR	5.2.4

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E FortiCache VM: FCH-VM64, FCH-KVM	4.1
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E FortiCache VM: FCH-VM64	4.0

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-2000E FortiProxy VM: FPX-KVM, FPX-VM64	1.0

Resolved Issues

The following issues have been fixed in FortiAnalyzer version 5.6.6. For inquiries about a particular bug, please contact [Customer Service & Support](#).

Event Management

Bug ID	Description
506196	Creating an event handler with Log match "Any of the following conditions" is not saved.

FortiView

Bug ID	Description
478609	Sorting Top Threats by Category in descending order are in alphabetic order.
483507	FortiAnalyzer returns Web Server Error404 error when downloading logs.

Log View

Bug ID	Description
480913	Timestamps are incorrect on FortiAnalyzer when Istanbul time zone is set on FortiGate.

Reports

Bug ID	Description
506431	IOC datasets should filter data for selected duration and show consistent results between FortiView and Report.
477569	After enabling the option, "Delete files(s) after uploading", in an output profile, FortiAnalyzer should delete all related files after uploaded the files to a server.

System Settings

Bug ID	Description
500225	The <i>Log Insert Lag Time</i> graph provides a completely different graph after every manual refresh.
501181	Log forwarding to <i>syslog</i> stops when <i>fwd-log-source-ip</i> is set as <i>original_ip</i> .

Others

Bug ID	Description
447910	In some occasions, retrieving log from FortiGate may cause the OFTPD daemon to consume high resources.
496713	FortiAnalyzer is showing an empty page when accessing via IPv6 using IE or Edge.

Common Vulnerabilities and Exposures

Visit <https://fortiguard.com/psirt> for more information.

Bug ID	Description
464795	FortiAnalyzer 5.6.6 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none">• CVE-2017-17541
473644	FortiAnalyzer 5.6.6 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none">• CVE-2018-1354
474994	FortiAnalyzer 5.6.6 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none">• CVE-2018-1355

Known Issues

The following issues have been identified in FortiAnalyzer version 5.6.6. For inquiries about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

System settings

Bug ID	Description
493249	FortiAnalyzer cluster may show the same serial number for Primary and Backup device.
508102	Log forwarding from FortiAnalyzer no longer includes timezone or offset.
515988	After modified the parameters for log storage policy, users may require rebooting FortiAnalyzer for the changes to take effect. The "diagnose log devices" command can confirm the current settings.



Copyright© 2018 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.